

PROJECT:

TYPE:

LOCATION:

CAT:



Description

Stand Alone DMX512 interface

Features

- Wall- mount extra thin housing (3/4")
- 512 in/Out PC and Stand Alone DMX channels (using no PC)
- SD Card reader
- 4 Mb of internal memory (min. capacity: 4,000 steps/512 ch)
- Splitter mode (2x512 DMX output)
- Automatic Scene Recovery if power is lost
- Scene Speed, manual color (RGBW), page, Dimmer modes
- 4 button navigation with LED display plus 8 trigger buttons
- Standard Mini USB 2.0 (Input)
- Ability to interconnect and synchronize up to 32 interfaces (32,768 DMX channels without PC use)
- Interface is compatible Windows and Mac Os X systems
- Contact closure for remote operation with 5 terminal pins

Mounting

Flush mount to wall or flat surface

Applications

Control of 1024 DMX addresses, upgradeable to 64 universes with additional hardware

Warranty

3 years



Technical Information

Power Input	9-36V DC, 0.5A max via DC connectors / 5V 0.5A via USB (power supply not included)
Power Consumption	0.3W - 0.5W
High Voltage Protection	Yes
Signal Input	USB 2.0 via Mini USB
DMX Output	1024 on 5 screw terminal pins
DMX Modes	2x512, 1024, or 512 in/out
DMX Input	Yes
Stand Alone Mode	Yes
Multiple Zone	Yes, 5 zones, can play 5 different scenes simultaneously
Contact Closure Function	On, On/Off, Release, Restart Scene
Internal Memory	4Mb
External Memory	Expandable with SD Card
Memory Capacity	up to 3,000 steps (with included memory)
Real Time Clock RTC	Time and Calendar triggers (minutes, hours, weeks, days, month)
CPU Technology	32bit
Master/Slave	Synchronize and connect up to 32 interfaces in stand alone
IP Rating	IP20 - Suitable for use in indoor, dry locations
Operating Temperature	-25°C (-13°F) to 70°C (158°F)
Weight	0.2Kgs (0.44Lbs)
Certifications	CE, RoHS, FCC

Software Information

Available to program with LED player for stand alone control
 Computer requirements Windows, Mac Os X (10.6 and higher) and Linux (64 bits)
 Additional factory programming can be obtained by contacting sales@prizmlighting.com

Ordering Information

DMX Wall Control



Includes:
1 USB Cable + 1 USB to DMX Interface

